



# Crossover Guide

**Commander SK & Unidrive SP to  
Unidrive M: Drives for Industry**  
Class-leading induction and servo permanent magnet  
motor performance, with real-time Ethernet

- Unidrive M100
- Unidrive M200
- Unidrive M300
- Unidrive M400
- Unidrive M600
- Unidrive M700

0.33 hp – 4,200 hp  
(0.25 kW – 2.8 MW) Heavy Duty  
100 V | 200 V | 400 V | 575 V | 690 V



# DIFFERENT APPLICATIONS, DIFFERENT NEEDS



**UNIDRIVE M**, drives for Industry: six unique models offer different levels of functionality.

Combine your Emerson drive with an Emerson Dyneo<sup>®</sup> motor, designed to work together for ultimate performance.

Find the perfect drive and motor combination for your application at [www.unidrivem.us](http://www.unidrivem.us)



Scan with your smart device to download our 'Discover Unidrive M' App

**Control Techniques™**  
**Leroy-Somer™**

## Commander SK to Unidrive M200, 120 to 230 V

### Dimensions

SK Frame	H x W x D (in)	H x W x D (in)	M200/M400 Frame	Retrofit Kit
A	6.1 x 3.0 x 5.7	6.3 x 3.0 x 5.1	1	NOT REQUIRED
B	8.1 x 3.4 x 6.2	8.1 x 3.1 x 5.9	2	NOT REQUIRED
C	10.2 x 3.9 x 6.8	8.9 x 3.5 x 6.3	3	3470-0097
D	13.2 x 4.5 x 7.8	10.9 x 4.5 x 6.9	4	3470-0101
2	15.3 x 6.1 x 8.6	15.4 x 5.6 x 7.6	5	3470-0066
3	15.3 x 9.8 x 10.2	15.4 x 8.3 x 9.0	6	3470-0074
4	21.5 x 12.2 x 11.7	21.9 x 10.6 x 11.0	7	3470-0078
5	33.8 x 12.2 x 11.7	31.7 x 12.2 x 11.4	8	3470-0087
6	46.0 x 12.2 x 11.7	43.6 x 12.2 x 11.4	9A	3470-0118



Commander SK

Unidrive M200

### Differences to Note:

- Unidrive M200 requires a RS485 Adaptor for Modbus communications
- Use Unidrive M400 for Commander SK + LogicStick replacements

### Power Specification

Input Voltage	HP	Commander SK			Unidrive M200		
		Output A	Frame	Order Code	Order Code	Output A	Frame
120 V 50/60 Hz, 1-Phase (230V, 3-Phase Output)	0.33	1.7	A	SKA1100025	M200-01100017A10101AB100	1.7	1
	0.5	2.2	A	SKA1100037	M200-01100024A10101AB100	2.4	1
	1	4	B	SKB1100075	M200-02100042A10101AB100	4.2	2
	1.5	5.2	B	SKB1100110	M200-02100056A10101AB100	5.6	2
200 - 240 V 50/60 Hz, 1-Phase	0.33	1.7	A	SKA1200025	M200-01200017A10101AB100	1.7	1
	0.5	2.2	A	SKA1200037	M200-01200024A10101AB100	2.4	1
	0.75	3	A	SKA1200055	M200-01200033A10101AB100	3.3	1
	1	4	A	SKA1200075	M200-01200042A10101AB100	4.2	1
	1.5	5.2	B	SKBD200110	M200-02200056A10101AB100	5.6	2
	2	7	B	SKBD200150	M200-02200075A10101AB100	7.5	2
	3	9.6	C	SKCD200220	M200-03200100A10101AB100	10	3
	3	12.6	D	SKDD200300	M200-04200133A10101AB100	13.3	4
200 - 240 V 50/60 Hz, 3-Phase	Not Available				M200-02200024A10101AB100	2.4	2
	Not Available				M200-02200033A10101AB100	3.3	2
	Not Available				M200-02200042A10101AB100	4.2	2
	1.5	5.2	B	SKBD200110	M200-02200056A10101AB100	5.6	2
	2	7	B	SKBD200150	M200-02200075A10101AB100	7.5	2
	3	9.6	C	SKCD200220	M200-03200100A10101AB100	10	3
	3	12.6	C	SKCD200300	M200-04200133A10101AB100	13.3	4
	5	17	D	SKD3200400	M200-04200176A10101AB100	17.6	4
	3	12.6	2	SK2201	M200-04200133A10101AB100	13.3	4
	5	17	2	SK2202	M200-04200176A10101AB100	17.6	4
	7.5	25	2	SK2203	M200-05200250A10101AB100	25	5
	10	31	3	SK3201	M200-06200330A10101AB100	33	6
	15	42	3	SK3202	M200-06200440A10101AB100	44	6
	20	56	4	SK4201	M200-07200610A10101AB100	61	7
25	68	4	SK4202	M200-07200750A10101AB100	75	7	
30	80	4	SK4203	M200-07200830A10101AB100	83	7	

This reference material provides an easy crossover based on hp/Amp ratings. Application specifics should be reviewed by an Emerson Application Engineer. For additional assistance, call 1 800 893 2321.

## Commander SK to Unidrive M200, 460 V

### Dimensions

SK Frame	H x W x D (in)	H x W x D (in)	M200/M400 Frame	Retrofit Kit
A	6.1 x 3.0 x 5.7	6.3 x 3.0 x 5.1	1	NOT REQUIRED
B	8.1 x 3.4 x 6.2	8.1 x 3.1 x 5.9	2	NOT REQUIRED
C	10.2 x 3.9 x 6.8	8.9 x 3.5 x 6.3	3	3470-0097
D	13.2 x 4.5 x 7.8	10.9 x 4.5 x 6.9	4	3470-0101
2	15.3 x 6.1 x 8.6	15.4 x 5.6 x 7.6	5	3470-0066
3	15.3 x 9.8 x 10.2	15.4 x 8.3 x 9.0	6	3470-0074
4	21.5 x 12.2 x 11.7	21.9 x 10.6 x 11.0	7	3470-0078
5	33.8 x 12.2 x 11.7	31.7 x 12.2 x 11.4	8	3470-0087
6	46.0 x 12.2 x 11.7	43.6 x 12.2 x 11.4	9A	3470-0118



Commander SK




Unidrive M200

### Differences to Note:

- Unidrive M200 requires a RS485 Adaptor for Modbus communications
- Use Unidrive M400 for Commander SK + LogicStick replacements

### Crossover Reference Table

Input Voltage	HP	Commander SK 			Unidrive M200		
		Output A	Frame	Order Code	Order Code	Output A	Frame
400 - 480 V 50/60 Hz, 3-Phase	0.5	1.3	B	SKB3400037	M200-02400013A10101AB100	1.3	2
	0.75	1.7	B	SKB3400055	M200-02400018A10101AB100	1.8	2
	1	2.1	B	SKB3400075	M200-02400023A10101AB100	2.3	2
	1.5	2.8	B	SKB3400110	M200-02400032A10101AB100	3.2	2
	2	3.8	B	SKB3400150	M200-02400041A10101AB100	4.1	2
	3	5.1	C	SKC3400220	M200-03400056A10101AB100	5.6	3
	3	7.2	C	SKC3400300	M200-03400073A10101AB100	7.3	3
	5	9	C	SKC3400400	M200-03400094A10101AB100	9.4	3
	7.5	13	D	SKD3400550	M200-04400135A10101AB100	13.5	4
	10	16.5	D	SKD3400750	M200-04400170A10101AB100	17	4
	7.5	13	2	SK2401	M200-04400135A10101AB100	13.5	4
	10	16.5	2	SK2402	M200-04400170A10101AB100	17	4
	15	25	2	SK2403	M200-05400270A10101AB100	27	5
	20	29	2	SK2404	M200-05400300A10101AB100	30	5
	25	32	3	SK3401	M200-06400350A10101AB100	35	6
	30	40	3	SK3402	M200-06400420A10101AB100	42	6
	30	46	3	SK3403	M200-06400470A10101AB100	46	6
	40	60	4	SK4401	M200-07400660A10101AB100	66	7
	50	74	4	SK4402	M200-07400770A10101AB100	77	7
	75	96	4	SK4403	M200-07401000A10101AB100	100	7
100	124	5	SK5401	M200-08401340A10101AB100	134	8	
125	156	5	SK5402	M200-08401570A10101AB100	157	8	
150	180	6	SK6401	M200-09402000A10101AB100	180	9	
150	210	6	SK6402	M200-09402240A10101AB100	211	9	

This reference material provides an easy crossover based on hp/Amp ratings. Application specifics should be reviewed by an Emerson Application Engineer. For additional assistance, call 1 800 893 2321.



## Commander SK to Unidrive M200, 575 to 690 V

### Dimensions

SK Frame	H x W x D (in)	H x W x D (in)	M200/400 Frame	Retrofit Kit
3	15.3 x 9.8 x 10.2	15.4 x 8.3 x 9.0	5	3470-0066
3	15.3 x 9.8 x 10.2	15.4 x 8.3 x 9.0	6	3470-0074
4	21.5 x 12.2 x 11.7	21.9 x 10.6 x 11.0	7	3470-0078
5	33.8 x 12.2 x 11.7	31.7 x 12.2 x 11.4	8	3470-0087
6	46.0 x 12.2 x 11.7	43.6 x 12.2 x 11.4	9A	3470-0118




Commander SK

Unidrive M200

### Differences to Note:

- Unidrive M200 requires a RS485 Adaptor for Modbus communications
- Use M400 for Commander SK + Logicstick replacements

### Crossover Reference Table

Input Voltage	HP	Commander SK				Unidrive M200	
		Output A	Frame	Order Code		Order Code	Output A
500 - 575 V 50/60 Hz, 3-Phase	2	4.1	3	SK3501	M200-05500030A10101AB100	3	5
	3	5.4	3	SK3502	M200-05500040A10101AB100	4	5
	5	6.1	3	SK3503	M200-05500069A10101AB100	6.9	5
	7.5	9.5	3	SK3504	M200-06500100A10101AB100	10	6
	10	12	3	SK3505	M200-06500150A10101AB100	15	6
	15	18	3	SK3506	M200-06500190A10101AB100	19	6
	20	22	3	SK3507	M200-06500230A10101AB100	23	6
	25	27	4	SK4603	M200-06500290A10101AB100	29	6
	30	36	4	SK4604	M200-06500350A10101AB100	34	6
	40	43	4	SK4605	M200-07500440A10101AB100	44	7
	50	52	4	SK4606	M200-07500550A10101AB100	55	7
	60	63	5	SK5601	M200-08500630A10101AB100	63	8
	75	85	5	SK5602	M200-08500860A10101AB100	86	8
	100	100	6	SK6601	M200-09501040A10101AB100	104	9
125	125	6	SK6602	M200-09501310A10101AB100	131	9	
500 - 690 V 50/60 Hz, 3-Phase	20	19	4	SK4601	M200-07600190A10101AB100	19	7
	25	22	4	SK4602	M200-07600240A10101AB100	24	7
	30	27	4	SK4603	M200-07600290A10101AB100	29	7
	40	36	4	SK4604	M200-07600380A10101AB100	38	7
	50	43	4	SK4605	M200-07600440A10101AB100	44	7
	60	52	4	SK4606	M200-07600540A10101AB100	54	7
	75	63	5	SK5601	M200-08600630A10101AB100	63	8
	100	85	5	SK5602	M200-08600860A10101AB100	86	8
	125	100	6	SK6601	M200-09601040A10101AB100	104	9
	150	125	6	SK6602	M200-09601310A10101AB100	131	9

This reference material provides an easy crossover based on hp/Amp ratings. Application specifics should be reviewed by an Emerson Application Engineer. For additional assistance, call 1 800 893 2321.

## Unidrive SP to Unidrive M701, 230 to 460 V, Normal Duty

### Dimensions

SP Frame	H x W x D (in)	H x W x D (in)	M701 Frame	Retrofit Kit
1	15.2 x 3.9 x 8.6	15.0 x 3.3 x 7.9	3	NOT REQUIRED
2	15.3 x 6.1 x 8.6	15.4 x 4.9 x 7.9	4	3470-0062
2	15.3 x 6.1 x 8.6	15.4 x 5.6 x 7.9	5	3470-0066
3	15.3 x 9.8 x 10.2	15.4 x 8.3 x 9.0	6	3470-0074
4	21.5 x 12.2 x 11.7	21.9 x 10.6 x 11.0	7	3470-0078
5	33.8 x 12.2 x 11.7	31.7 x 12.2 x 11.4	8	3470-0087
6	46.0 x 12.2 x 11.7	43.6 x 12.2 x 11.4	9A	3470-0118




Unidrive SP    Unidrive M701

### Differences to Note:

- For Unidrive SP applications with SM-Ethernet use M700 drives
- Unidrive M70x drives do not include a keypad, order separately
- Add SI-I/O option for Unidrive M701 high resolution analog input

### Crossover Reference Table

Input Voltage	HP	Unidrive SP				Unidrive M701	
		Output A	Frame	Order Code		Order Code	Output A
200 - 240 V 50/60 Hz, 3-Phase	1.5	5.2	1	SP1201	M701-03200050A10101AB100	6.6	3
	2	6.8	1	SP1202	M701-03200066A10101AB100	8	3
	3	9.6	1	SP1203	M701-03200080A10101AB100	11	3
	3	11	1	SP1204	M701-03200106A10101AB100	12.7	3
	5	15.5	2	SP2201	M701-04200137A10101AB100	18	4
	7.5	22	2	SP2202	M701-04200185A10101AB100	25	4
	10	28	2	SP2203	M701-05200250A10101AB100	30	5
	15	42	3	SP3201	M701-06200330A10101AB100	50	6
	20	54	3	SP3202	M701-06200440A10101AB100	58	6
	25	68	4	SP4201	M701-07200610A10101AB100	75	7
	30	80	4	SP4202	M701-07200750A10101AB100	94	7
	40	104	4	SP4203	M701-07200830A10101AB100	117	7
	50	130	5	SP5201	M701-08201160A10101AB100	149	8
	60	154	5	SP5202	M701-08201320A10101AB100	180	8
380 - 460 V 50/60 Hz, 3 Phase	1.5	2.8	1	SP1401	M701-03400025A10101AB100	3.4	3
	2	3.8	1	SP1402	M701-03400031A10101AB100	4.5	3
	3	5	1	SP1403	M701-03400045A10101AB100	6.2	3
	5	6.9	1	SP1404	M701-03400062A10101AB100	7.7	3
	5	8.8	1	SP1405	M701-03400078A10101AB100	10.4	3
	7.5	11	1	SP1406	M701-03400100A10101AB100	12.3	3
	10	15.3	2	SP2401	M701-04400150A10101AB100	18.5	4
	15	21	2	SP2402	M701-04400172A10101AB100	24	4
	20	29	2	SP2403	M701-05400270A10101AB100	30	5
	20	29	2	SP2404	M701-05400300A10101AB100	31	5
	25	35	3	SP3401	M701-06400350A10101AB100	38	6
	30	43	3	SP3402	M701-06400420A10101AB100	48	6
	40	56	3	SP3403	M701-06400470A10101AB100	63	6
	50	68	4	SP4401	M701-07400660A10101AB100	79	7
	60	83	4	SP4402	M701-07400770A10101AB100	94	7
	75	104	4	SP4403	M701-07401000A10101AB100	112	7
	100	138	5	SP5401	M701-08401340A10101AB100	155	8
	125	168	5	SP5402	M701-08401570A10101AB100	184	8
150	205	6	SP6401	M701-09402000A10101AB100	221	9	
200	236	6	SP6402	M701-09402240A10101AB100	255	9	

This reference material provides an easy crossover based on hp/Amp ratings. Application specifics should be reviewed by an Emerson Application Engineer. For additional assistance, call 1 800 893 2321.

## Unidrive SP to Unidrive M701, 230 to 460 V, Heavy Duty

### Dimensions

SP Frame	H x W x D (in)	H x W x D (in)	M701 Frame	Retrofit Kit
1	15.2 x 3.9 x 8.6	15.0 x 3.3 x 7.9	3	NOT REQUIRED
2	15.3 x 6.1 x 8.6	15.4 x 4.9 x 7.9	4	3470-0062
2	15.3 x 6.1 x 8.6	15.4 x 5.6 x 7.9	5	3470-0066
3	15.3 x 9.8 x 10.2	15.4 x 8.3 x 9.0	6	3470-0074
4	21.5 x 12.2 x 11.7	21.9 x 10.6 x 11.0	7	3470-0078
5	33.8 x 12.2 x 11.7	31.7 x 12.2 x 11.4	8	3470-0087
6	46.0 x 12.2 x 11.7	43.6 x 12.2 x 11.4	9A	3470-0118




Unidrive SP    Unidrive M701

### Differences to Note:

- For Unidrive SP applications with SM-Ethernet use M700 drives
- Unidrive M70x drives do not include a keypad, order separately
- Add SI-I/O option for Unidrive M701 high resolution analog input

### Crossover Reference Table

Input Voltage	HP	Unidrive SP 			Unidrive M701		
		Output A	Frame	Order Code	Order Code	Output A	Frame
200 - 240 V 50/60 Hz, 3-Phase	1	4.3	1	SP1201	M701-03200050A10101AB100	5	3
	1.5	5.8	1	SP1202	M701-03200066A10101AB100	6.6	3
	2	7.5	1	SP1203	M701-03200080A10101AB100	8	3
	3	10.6	1	SP1204	M701-03200106A10101AB100	10.6	3
	3	12.6	2	SP2201	M701-04200137A10101AB100	13.7	4
	5	17	2	SP2202	M701-04200185A10101AB100	18.5	4
	7.5	25	2	SP2203	M701-05200250A10101AB100	25	5
	10	31	3	SP3201	M701-06200330A10101AB100	33	6
	15	42	3	SP3202	M701-06200440A10101AB100	44	6
	20	56	4	SP4201	M701-07200610A10101AB100	61	7
	25	68	4	SP4202	M701-07200750A10101AB100	75	7
	30	80	4	SP4203	M701-07200830A10101AB100	83	7
	40	105	5	SP5201	M701-08201160A10101AB100	116	8
	50	130	5	SP5202	M701-08201320A10101AB100	132	8
380 - 460 V 50/60 Hz, 3 Phase	1	2.1	1	SP1401	M701-03400025A10101AB100	2.5	3
	1.5	3	1	SP1402	M701-03400031A10101AB100	3.1	3
	2	4.2	1	SP1403	M701-03400045A10101AB100	4.5	3
	3	5.8	1	SP1404	M701-03400062A10101AB100	6.2	3
	5	7.6	1	SP1405	M701-03400078A10101AB100	7.8	3
	5	9.5	1	SP1406	M701-03400100A10101AB100	10	3
	7.5	13	2	SP2401	M701-04400150A10101AB100	15	4
	10	16.5	2	SP2402	M701-04400172A10101AB100	17.2	4
	15	25	2	SP2403	M701-05400270A10101AB100	25.4	5
	20	29	2	SP2404	M701-05400300A10101AB100	30	5
	25	32	3	SP3401	M701-06400350A10101AB100	35	6
	30	40	3	SP3402	M701-06400420A10101AB100	42	6
	30	46	3	SP3403	M701-06400470A10101AB100	46	6
	40	60	4	SP4401	M701-07400660A10101AB100	66	7
	50	74	4	SP4402	M701-07400770A10101AB100	77	7
	75	96	4	SP4403	M701-07401000A10101AB100	100	7
	100	124	5	SP5401	M701-08401340A10101AB100	134	8
	125	156	5	SP5402	M701-08401570A10101AB100	157	8
150	180	6	SP6401	M701-09402000A10101AB100	180	9A	
150	210	6	SP6402	M701-09402240A10101AB100	211	9A	

This reference material provides an easy crossover based on hp/Amp ratings. Application specifics should be reviewed by an Emerson Application Engineer. For additional assistance, call 1 800 893 2321.

## Unidrive SP to Unidrive M701, 575 to 690 V, Heavy Duty

### Dimensions

SP Frame	H x W x D (in)	H x W x D (in)	M701 Frame	Retrofit Kit
N/A	N/A	15.4 x 5.6 x 7.9	5	3470-0066
3	15.3 x 9.8 x 10.2	15.4 x 8.3 x 9.0	6	3470-0074
4	21.5 x 12.2 x 11.7	21.9 x 10.6 x 11.0	7	3470-0078
5	33.8 x 12.2 x 11.7	31.7 x 12.2 x 11.4	8	3470-0087
6	46.0 x 12.2 x 11.7	43.6 x 12.2 x 11.4	9A	3470-0118

### Differences to Note:


- For Unidrive SP applications with SM-Ethernet use M700 drives
- Unidrive M70x drives do not include a keypad, order separately
- Add SI-I/O option for Unidrive M701 high resolution analog input



Unidrive SP

Unidrive M701

### Crossover Reference Table

Input Voltage	HP	Unidrive SP 			Unidrive M701		
		Output A	Frame	Order Code	Order Code	Output A	Frame
500 - 575 V 50/60 Hz, 3-Phase	2	4.1	3	SP3501	M701-05500030A10101AB100	3	5
	3	5.4	3	SP3502	M701-05500040A10101AB100	4	5
	5	6.1	3	SP3503	M701-05500069A10101AB100	6.9	5
	7.5	9.5	3	SP3504	M701-06500100A10101AB100	10	6
	10	12	3	SP3505	M701-06500150A10101AB100	15	6
	15	18	3	SP3506	M701-06500190A10101AB100	19	6
	20	22	3	SP3507	M701-06500230A10101AB100	23	6
	25	27	4	SP4603	M701-06500290A10101AB100	29	6
	30	36	4	SP4604	M701-06500350A10101AB100	34	6
	40	43	4	SP4605	M701-07500440A10101AB100	44	7
	50	52	4	SP4606	M701-07500550A10101AB100	55	7
	60	63	5	SP5601	M701-08500630A10101AB100	63	8
	75	85	5	SP5602	M701-08500860A10101AB100	86	8
	100	100	6	SP6601	M701-09501040A10101AB100	104	9
125	125	6	SP6602	M701-09501310A10101AB100	131	9	
500 - 690 V 50/60 Hz, 3-Phase	20	19	4	SP4601	M700-07600190A10101AB100	19	7
	25	22	4	SP4602	M700-07600240A10101AB100	24	7
	25	27	4	SP4603	M700-07600290A10101AB100	29	7
	30	36	4	SP4604	M700-07600380A10101AB100	38	7
	40	43	4	SP4605	M700-07600440A10101AB100	44	7
	50	52	4	SP4606	M700-07600540A10101AB100	54	7
	60	63	5	SP5601	M700-08600630A10101AB100	63	8
	75	85	5	SP5602	M700-08600860A10101AB100	86	8
	100	100	6	SP6601	M700-09601040A10101AB100	104	9
125	125	6	SP6602	M700-09601310A10101AB100	131	9	

This reference material provides an easy crossover based on hp/Amp ratings. Application specifics should be reviewed by an Emerson Application Engineer. For additional assistance, call 1 800 893 2321.



## Unidrive SP to Unidrive M701, 575 to 690 V, Normal Duty

### Dimensions

SP Frame	H x W x D (in)	H x W x D (in)	M701 Frame	Retrofit Kit
3	15.3 x 9.9 x 10.3	15.4 x 5.6 x 7.9	5	3470-0066
4	21.5 x 12.2 x 11.7	15.4 x 8.3 x 8.9	6	3470-0074
5	33.8 x 12.2 x 11.7	21.9 x 10.6 x 11	7	3470-0078
6	46 x 12.2 x 11.7	31.6 x 12.2 x 11.4	8	3470-0087
			9A	3470-0118




Unidrive SP

Unidrive M701

### Differences to Note:

- For Unidrive SP applications with SM-Ethernet use M700 drives
- Unidrive M70x drives do not include a keypad, order separately
- Add SI-I/O option for Unidrive M701 high resolution analog input

### Crossover Reference Table

Input Voltage	HP	Unidrive SP 			Unidrive M701		
		Output A	Frame	Order Code	Order Code	Output A	Frame
500 - 575 V 50/60 Hz, 3-Phase	3	5.4	3	SP3501	M701-05500030A10101AB100	3.9	5
	5	6.1	3	SP3502	M701-05500040A10101AB100	6.1	5
	7.5	8.4	3	SP3503	M701-05500069A10101AB100	10	5
	10	11	3	SP3504	M701-06500100A10101AB100	12	6
	15	16	3	SP3505	M701-06500150A10101AB100	17	6
	20	22	3	SP3506	M701-06500190A10101AB100	22	6
	25	27	3	SP3507	M701-06500230A10101AB100	27	6
	30	36	4	SP4603	M701-06500290A10101AB100	34	6
	40	43	4	SP4604	M701-06500350A10101AB100	43	6
	50	52	4	SP4605	M701-07500440A10101AB100	53	7
	60	62	4	SP4606	M701-07500550A10101AB100	73	7
	75	84	5	SP5601	M701-08500630A10101AB100	86	8
	100	99	5	SP5602	M701-08500860A10101AB100	108	8
	125	125	6	SP6601	M701-09501040A10101AB100	125	9
	150	144	6	SP6602	M701-09501310A10101AB100	150	9
500 - 690 V 50/60 Hz, 3-Phase	25	22	4	SP4601	M701-07600190A10101AB100	23	7
	30	27	4	SP4602	M701-07600240A10101AB100	30	7
	30	36	4	SP4603	M701-07600290A10101AB100	36	7
	40	43	4	SP4604	M701-07600380A10101AB100	46	7
	50	52	4	SP4605	M701-07600440A10101AB100	52	7
	60	62	4	SP4606	M701-07600540A10101AB100	73	7
	75	84	5	SP5601	M701-08600630A10101AB100	88	8
	100	99	5	SP5602	M701-08600860A10101AB100	108	8
	125	125	6	SP6601	M701-09601040A10101AB100	125	9
150	144	6	SP6602	M701-09601310A10101AB100	155	9	

This reference material provides an easy crossover based on hp/Amp ratings. Application specifics should be reviewed by an Emerson Application Engineer. For additional assistance, call 1 800 893 2321.

## Option Modules, Software, Keypads & Cloning



Function	SM Option Modules	SI Option Modules	Notes
	SK/SP* 	Unidrive M	
	Order Code	Order Code	
Inputs/Outputs	SM-BIPOLAR	Not available	
	SM-I/O-120V	Not available	
	SM-I/O-24V	SI-I/O	24 Vdc I/O unprotected
	SM-I/O-32	Not available	
	SM-I/O-LITE	SI-I/O	
	SM-I/O-TIMER	SI-I/O	Requires KI-KEYPAD-RTC or REMOTE-KEYPAD-RTC
	SM-I/O-PLUS	SI-I/O	
Communications	SM-I/O-PELV	Not available	
	SM-CAN	Not available	
	SM-CANOPEN	SI-CANOPEN	
	SM-DEVICENET	SI-DEVICENET	
	SM-ETHERCAT	SI-ETHERCAT	
	SM-ETHERNET	SI-ETHERNET	Unidrive M700, M702 include Ethernet as standard
	SM-INTERBUS	Not available	
	SM-PROFIBUS-DP	SI-PROFIBUS	
Feedback	SM-PROFINET	SI-PROFINET-V2	
	SM-SERCOS	Not available	
	SM-ETC	SM-ETC	
	SM-ENCODER-PLUS	SI-ENCODER	
	SM-ENCODER-OUT	SI-UNI-ENCODER	Unidrive M700, M701, M702 include encoder output as standard
Automation	SM-UNI-ENCODER	SI-UNI-ENCODER	
	SM-RESOLVER	Not required	Unidrive M700, M701, M702 include resolver input as standard
	LOGICKSTICK	Not required	For new applications use Unidrive M400
	SM-APPS-LITE-V2	SI-APPS-PLUS	For new applications use MCI200
	SM-APPS-PLUS	SI-APPS-PLUS	For new applications use MCI210
Safety	SM-EZMOTION	see note	Use Unidrive SP-EZ part number SPxxxx-EZ
	SM-REGISTER	SI-APPS-PLUS	For new applications use MCI210
Software	SM-SAFETY	SI-SAFETY	Unidrive M600, M700, M701 and M702 only
	CTSOFT	UNIDRIVE M CONNECT	Unidrive M Connect can import CTSoft files
	CTSCOPE	CTSCOPE	
	SYPT-LITE	MACHINE CONTROL STUDIO	Onboard PLC programming (M400 - M702) and MCI2x0
	SYPTPRO	SYPTPRO	For new applications use MCI200 & MCI210 options programmed with MACHINE CONTROL STUDIO
Keypads	CTSAFEPRO	CTSAFEPRO	Programming software for SI-Safety
	Not available	REMOTE-KEYPAD-RTC	
	SK-KEYPAD-REMOTE	REMOTE-KEYPAD	Requires RS485 port
	SM-KEYPAD	KI-KEYPAD-LCD	
	SM-KEYPAD-PLUS	KI-KEYPAD-LCD	Use REMOTE-KEYPAD(-RTC) for remote mounting
Cloning	Not available	CI-KEYPAD-LCD	Unidrive M400 keypad
	SMARTCARD	SMARTCARD-64	64k Smartcard
		SD-CARD-ADAPTOR SMARTCARD	Smartcard with SD card adaptor
		SMARTCARD	8k Smartcard
Cables	SMARTSTICK	AI-BACKUP-ADAPTOR	Requires SD card (not included)
		AI-SMART-ADAPTOR	Includes 4GB SD card
	CT-USB-CABLE	CT-USB-CABLE	AI-485-ADAPTOR and Unidrive M600 and M701

### Differences to Note:

- SM and SI Option modules are not interchangeable
- MCI200 and MCI210 options are programmed using Machine Control Studio software
- SYPT-PRO can only be used to program SI-APPS-PLUS modules
- SYPT-LITE can not be used with Unidrive M products

\* SK = Commander SK  
SP = Unidrive SP



KI-KEYPAD and REMOTE-KEYPAD-RTC



**Control Techniques™**

**Leroy-Somer™**

[www.controltechniques.com](http://www.controltechniques.com)

This reference material provides an easy crossover based on horsepower (hp)/Amp ratings. Application specifics should be reviewed by an Emerson Application Engineer.

For additional assistance, call 1 800 893 2321.

The information contained in this brochure is for guidance only and does not form part of any contract. The accuracy cannot be guaranteed as Control Techniques have an ongoing process of development and reserve the right to change the specification of their products without notice.